


Cisco 8832 Series | Quick Start Guide



Your Phone

- 1 LED bar
- (2) Wired microphone ports
- (3) Mute bar
- (4) Softkey buttons
- (5) Navigation bar and Select button
- 6 Volume key

LED Bar States

The LED bar illuminates to indicate status:

- · Green, solid-Active call
- · Green, flashing-Incoming call
- · Green, pulsing-Held call
- · Red, solid-Muted call

Make a Call

Enter a number and press Call.

Answer a Call

Press Answer.

Put a Call on Hold

- 1. Press Hold.
- 2. To resume a call from hold, press Resume.

View Your Recent Calls

Press Recents or press the up navigation key.

View Your Favorites

Press **Favorites** or press the down navigation key to see your speed-dial numbers.

Add Another Person to a Call

- 1. From an active call, press Conference.
- 2. Enter a number.
- 3. (Optional) Wait until you hear ringing or until the other person answers the call.
- 4. Press Conference.



Cisco 8832 Series | Quick Start Guide

Transfer a Call to Another Person

- 1. From a call that is not on hold, press Transfer.
- 2. Enter the other person's phone number.
- 3. (Optional) Wait until you hear ringing or until the other person answers the call.
- 4. Press Transfer again.

Mute Your Call

- 1. Press Mute on the phone or Mute on the extension microphone.
- 2. Press Mute again to turn mute off.

Listen to Voice Messages

Press Messages and follow the voice prompts.

Forward All Calls

- 1. Press Forward all.
- Dial the number that you want to forward to, or press Message.
- 3. When you return, press Forward off.

Adjust the Volume in a Call

Press Volume up or down to adjust the volume when the phone is in use.

Adjust the Ringer Volume

Press Volume up or down to adjust the ringer volume when the phone is not in use.

Change the Ringtone

- 1. Select Settings > Preferences > Ringtone.
- 2. Scroll through the list of ringtones and press **Play** to hear a sample.
- 3. Press Set to save a selection.

Change the Brightness

- 1. Select Settings > Preferences > Brightness
- 2. Press the navigation bar up to increase brightness and down to decrease brightness.
- 3. Press Save.

Pair a Wireless Microphone

- Select Settings > Admin Settings > Microphones > Wireless Microphone.
- 2. Select either **Microphone 1** or **Microphone 2**, and press **Pair**.
- 3. Press **Mute** on the wireless microphone until the microphone LED blinks white.

Unpair a Wireless Microphone

- Select Settings > Admin Settings > Microphones > Wireless Microphone.
- 2. Select either Microphone 1 or Microphone 2.
- 3. Press Unpair on the base unit.

Charge a Wireless Microphone

- 1. Place the microphone in the charging cradle.
- 2. If the LED is not white, remove the microphone and replace it in the cradle.

Cisco and the Cisco logo are trademarks or registered trademarks of Cisco and/or its affiliates in the U.S. and other countries. To view a list of Cisco trademarks, go to this URL: www.cisco.com/go/trademarks. Third-party trademarks mentioned are the property of their respective owners. The use of the word partner does not imply a partnership relationship between Cisco and any other company. (1110R)